



Quality and reliability is our tradition

KYORITSU

120A AC/DC Digital Multimeter with Open Clamp Sensor

KEW MATE 2012R

Convenient
for current
measurement
at the crowded
connection box!

Fit into
your pocket

True-RMS

AC/DC-current
measurement
up to 120A!

Max
resolution:
0.01A!

Measuring
conductor
diameter:
 ϕ 12mm

Equipped
with a shock
absorbing holster



TRUE RMS



AC A	60.00/120.0A
DC A	60.00/120.0A
AC V	6.000/60.00/600.0V
DC V	600.0mV/6.000/60.00/600.0V
Ω	600.0 Ω /6.000/60.00/600.0k Ω /6.000/60.00M Ω
Continuity buzzer	Buzzer sounds below 35 \pm 25 Ω
Diode test	2V
Capacitance	400.0nF/4.000/40.00 μ F
Frequency	(AC A) 100/1000Hz/10kHz (AC V) 100/1000Hz/10/100/300.0kHz
Conductor size	ϕ 12mm max.
Power source	R03 (1.5V) \times 2
Dimensions/Weight	128(L) \times 92(W) \times 27(D)mm/ Approx.220g (including batteries)

*The contents of this leaflet are subject to change without notice



KYORITSU ELECTRICAL INSTRUMENTS WORKS, LTD.

No.5-20,Nakane 2-chome, Meguro-ku, Tokyo, 152-0031 Japan

Phone: +81-3-3723-0131 Fax: +81-3-3723-0152

URL: <http://www.kew-ltd.co.jp>

E-mail: info@kew-ltd.co.jp

YH10082009