
SmartEAR



Technical data

| Mechanics | |
|------------------------|--|
| Protection class | IP 68 |
| Operating temperature | -20° C +70° C |
| Storage temperature | -20° C +70° C |
| Display | Blue LED |
| Commissioning | Via smartphone app SmartEAR-GO! |
| Electronics | |
| Processor | 32 bit |
| Anti-theft protection | Motion sensor |
| On/off | Magnetic switch |
| Power supply | |
| Power supply | Lithium battery 3.6 V / 13 Ah |
| Battery lifetime | Up to 9 years |
| Battery change | Possible on site |
| Measuring modes | |
| Night measurement | Between 2 am - 4 am |
| Permanent measurement | Every 15 minutes / hourly upload |
| Customised measurement | Multiple measurement cycles, freely selectable upload times and lengths of audio files |
| Communication | |
| Long-range radio | NB-IoT, LTE-M (combi-modem) |
| Short-range radio | Bluetooth® Low Energy |
| Transmission protocol | MQTT |
| Housing | |
| Height | 122 mm |
| Diameter | 69 mm (79 mm max.) |
| Weight | 450 g |
| Material | A2 stainless steel, PPH and PPS |
| Mounting options | Magnet, magnetic ring, threaded adapter |
| Anti-theft protection | Stainless steel cable |





Scope of delivery

| Product | Order number |
|---|--------------|
| SmartEAR, NB-IoT noise logger without SIM card | 1014081 |
| with loop, rod antenna, magnetic adapter and battery | |
| SmartEAR, NB-IoT noise logger with SIM card (Telekom EU) | 1014081-001 |
| with loop, rod antenna, magnetic adapter and battery | |
| SmartEAR, NB-IoT noise logger with SIM card (Vodafone) | 1014081-002 |
| with loop, rod antenna, magnetic adapter and battery | |
| SmartEAR, NB-IoT noise logger with SIM card (O2 Telefonica) | 1014081-003 |
| with loop, rod antenna, magnetic adapter and battery | |
| SmartEAR, NB-IoT noise logger with SIM card (Telekom EU extended) | 1014081-004 |
| with loop, rod antenna, magnetic adapter and battery | |
| SmartEAR, NB-IoT noise logger with SIM card (Telekom North America) | 1014081-005 |
| with loop, rod antenna, magnetic adapter and battery | |
| SmartEAR, NB-IoT noise logger with SIM card (Telekom Global) | 1014081-006 |
| with loop, rod antenna, magnetic adapter and battery | |
| Optional accessories | |
| Transport box for 10 SmartEAR loggers | 2014649 |
| Anti-theft stainless steel cable | 2015049 |
| Magnetic ring | 2015069 |
| Magnet adapter 32/14 220N, Neodym Magnet | 820015167 |
| Rod antenna LTE NB-IoT SMA-M 698-960MHz | 90035958 |
| Antenna extension GT-3-1-AV, 300 cm | 2011249 |
| SAFT lithium battery 3,6 V / LSH-20 size D | 820007318 |




Transport box with space for 10 SmartEAR loggers and with extra compartment



Magnetic ring (360° free adjustable)



Magnet ring with anti-theft stainless steel cable



Magnet adapter (automatically included with every SmartEAR logger)




Rod antenna



Antenna extension (300 cm)



SAFT lithium battery



Thread adapter / Composite hydrant lid

SebaKMT

Megger Germany GmbH \cdot Dr.-Herbert-lann-Str.6 \cdot D-96148 Baunach Tel. +49 95 44 - 6 80 \cdot Fax +49 95 44 - 22 73 sales@sebakmt.com \cdot www.sebakmt.com

